




## R-Smart<sup>1510</sup>



### R-Series Advanced Power Protection

A full line of products designed for the modern family with advanced features and characteristics needed for today's modern devices.






## Smart UPS with Voltage Regulator


The R-Smart series features unsurpassed reliability for regions or countries with severe, chronic voltage problems. The built in voltage regulator has a very wide range of operation to correct brownout and high voltage conditions without using the battery. In the event that the voltage surpasses the set point or a blackout occurs the R-Smart will instantly switch to battery and provide up to 45 minutes\* of battery power for you to save all of your open files.

\* Calculated with a basic PC and a 15" LCD monitor. Approximate time.

**Front View**



**Rear View**



**Touch Screen LCD Display**



CDP



Output Voltage



Input Voltage



Load Percent



Battery Percent

**MODEL**

**R-Smart 1510**

Capacity	1500VA/ 900W	
Input	Voltage	120Vac
	Frequency	50/60 Hz +/- 3%
	Voltage Range	81-145 Vca
	Max. Input current (Bypass)	15 Amps / 1800 W
Output	Voltage	120Vac
	AC Voltage Regulation	+/- 10%
	Frequency Range	60Hz +/- 1Hz
	Waveform	Simulated Sinewave
	Transfer Time	2-4ms [Tipico]
	Outlets Nema 5-15R	5pcs Batery backup+ 5pcs surge protected
	Maximum current	7.5 A
Battery	Battery Type & Number	12V/9AH x 2
	Recharge Time	5 Batery backup and Avr / 5 Surge only
Indicators	LCD indicator	AC mode \ BAT mode \ overload \ AVR mode \ fault \ input voltage \ output voltage \ output fre \ load percent \ battery capacity
Protection	Full Protection	Overload, discharge, and overcharge protection
Alarm	Battery Mode	Sounding every 10 seconds
	Low Battery	Sounding every second
	Overload	Sounding every 0.5 second
	Battery Replacement	Sounding every 2 seconds
	Fault	Continuously sounding
Physical	Dimensions (LxHxD)	390*146*200mm
	Net Weight (kgs)	12 Kg
Environment	Humidity	0-90 % RH @0-40°C (non-condensing)
	Noise Level	Less than 45dB
Management	USB/RS-232 Port	Supports Windows® 2000/2003/XP/Vista/2008/7, Linux, Unix, and MAC

"Specifications subject to change without notice"

**Bolivia:** 800-100156   **Colombia:** 01800-5181617   **Costa Rica:** 800-4357237   **El Salvador:** 800-6773   **Honduras:** 800-25616099

**México:** 001800 514 8611   **Panamá:** 011-00800-2268611   **Perú:** 0800-54674   **República Dominicana:** 1888-7514876   **Venezuela:** 0800-1627485

